


Positive-Voltage Regulators

- 3-Terminal Regulators
- Output Current up to 100 mA
- No External Components
- Internal Thermal-Overload Protection
- Internal Short-Circuit Current Limiting
- Provided Pb-Free packages from the end of 2004

description

This series of fixed-voltage integrated-circuit voltage regulators is designed for a wide range of applications. These applications include on-card regulation for elimination of noise and distribution problems associated with single-point regulation. In addition, they can be used with power-pass elements to make high-current voltage regulators. One of these regulators can deliver up to 100 mA of output current. The internal limiting and thermal-shutdown features of these regulators make them essentially immune to overload. When used as a replacement for a zener diode-resistor combination, an effective improvement in output impedance can be obtained, together with lower bias current.





SOT-89 78L09CPK

electrical characteristics at specified virtual junction temperature, V_{I} = 16V, I_{o} =40mA (unless otherwise noted)

| PARAMETER | TEST CONDITIONS | т‡ | 78L09 | | | UNIT |
|------------------------------|---------------------------------------|------------|-------|-----|------|------|
| | | | MIN | TYP | MAX | |
| Output voltage | | 25°C | 8.6 | 9 | 9.4 | V |
| | lo=1mA to 40MA, V1= 12V to 24V | Ful range | 8.55 | 9 | 9.45 | |
| | IO = 1 mA to 70 mA | Fullrange | 8.55 | 9 | 9.45 | |
| Input voltage regulation | Vj= 12V to 24V | 25°C | 11 10 | 45 | 175 | mV |
| | VI = 13V to 24V | | | 40 | 125 | |
| Ripple rejection | V _I =15V to 25V F = 120 Hz | 25°C | 38 | 45 | | dB |
| Output voltage regulation | IO = 1 mA to 100 mA | 25°C | | 19 | 90 | |
| | IO = 1 mA to 40 mA | | | 11 | 40 | m۷ |
| Output noise voltage | F = 10 Hz to 100 kHz | 25°C | | 58 | | μV |
| Dropout voltage | | 25°C | | 1.7 | | V |
| Bias current | | 25°C | | 4.1 | - 6 | mA |
| | | 125°C | | | 5.5 | |
| Bias current change | V ₁ =13V to 24V | Full range | | | 1.5 | mA |
| | IO = 1 mA to 40 mA | | | | 0.1 | |

‡ Pulse testing techniques maintain T_J as close to T_A as possible. Thermal effects must be taken into account separately. All characteristics are measured with a 0.33-μF capacitor across the input and a 0.1-μF capacitor across the output. Full range for the 78L05 is T_J = 0°C to 70°C